

Converters  
**IndraDrive C**  
**HCS02**



Converters

**IndraDrive C ■ HCS02**

- Continuous output from 1.5 kW to 11 kW
- Overload capacity 2.5x
- Maximum current from 12 A to 70 A
- Can be connected to inverters for cost-effective solutions
- Direct mains connection from 200 V to 500 V

**Documentation**

- Application description
- Project planning manual
- Firmware

The HCS02 converter from the IndraDrive C series integrates inverter and power supply in one unit. The compact construction contains additional mains connection components, making it particularly suitable for single-axis applications.

**Technical data**

		HCS02.1E-W0012	HCS02.1E-W0028	HCS02.1E-W0054	HCS02.1E-W0070
<b>Performance data</b>					
Continuous current	[A]	4.5	12	20.6	28
Maximum current	[A]	11.5	28.3	54	70.8
Motor rated capacity, typical	[kW]	1.5	4	7.5	11
Mains voltage	1 AC	200...250 V			
	3 AC	200...500 V			
Tolerance	[%]	± 10 %			
Frequency		50...60 Hz			
Frequency tolerance	[Hz]	± 2 Hz			
Continuous current mains input	[A]	6	13	20	30
Power dependency from the supply voltage	$U_{LN} < 400 \text{ V}$	1% power reduction per 4 V			
	$U_{LN} > 400 \text{ V}$	1% power gain per 5 V			
Mains contactor		External			
<b>Intermediate circuit</b>					
Continuous power with choke	[kW]	2.1	5.1	10	14
Max. power with choke	[kW]	5	10	16	19
Continuous power without choke	[kW]	2.1	5.1	7	9
Max. power without choke	[kW]	5	8	12	14

## Converters

## IndraDrive C ■ HCS02

Switching frequency/max. output frequency	4 kHz	0 ... 400 Hz			
	8 kHz	0 ... 800 Hz			
	12 kHz	0...1200 Hz			
	16 kHz	0...1600 Hz			
Output voltage	[V]	3 x AC 0 V to mains connection voltage			
Intermediate circuit capacity	[mF]	0.135	0.27	0.54	0.675
DC bus voltage	[V] DC	Mains connection voltage x 1.41			
Ability to combine converter/inverter		●			
<b>Brake chopper / resistor</b>					
Braking resistance		Internal		Internal/external	
Brake chopper		Internal			
Braking energy consumption	[kWs]	1	5	9	13
Continuous braking power	[kW]	0.05	0.15	0.35	0.5
Maximum braking power	[kW]	4	10	18	25
<b>Control voltage</b>					
Power consumption without control unit and motor brake	[W]	12	14	23	
<b>Protection</b>					
Overall protection category		IP20			
EMC		EN 61800-3 <sup>↔</sup>			
Cooling type		Air cooling			
<b>Norms and Standards</b>					
Certification		EN 61800-3 <sup>↔</sup> EN 61800-5-1 <sup>↔</sup> UL 508 C <sup>↔</sup> C22.2 No. 14-05			
<b>Weight</b>					
Weight	[kg]	2.9	3.8	6.7	6.8

All data for nominal rating at 3 AC 400 V mains voltage and 4 kHz switching frequency

## Dimensions

		HCS02.1E-W0012	HCS02.1E-W0028	HCS02.1E-W0054	HCS02.1E-W0070
<b>Dimensions</b>					
Height H	[mm]	290	352	352	352
Width B	[mm]	65	65	105	105
Depth T	[mm]	252	252	252	252

Converters

**IndraDrive C ■ HCS02****Components****Control units**

Description	Page	Details
Servo drives	Firmware 1G	IndraDrive (MPH, MPB, MPD, MPC)
Servo drives	Firmware 2G	IndraDrive (MPE, MPB/MPM, MPC)
Servo drives	Control units 1G	IndraDrive (BASIC, ADVANCED)
Servo drives	Control units 2G	IndraDrive (ECONOMY, BASIC, ADVANCED)

**Accessories****Auxiliary components**

Description		
Accessories	Brake units	HLB01
Accessories	Brake resistors	HLR01
Accessories	Motor filters	HMF01
Accessories	Mains chokes	HNL01/02
Accessories	Mains filter	HNF01
Accessories	Capacity module	HLC01

All data for nominal rating at 3 AC 400 V mains voltage and 4 kHz switching frequency

**Bosch Rexroth AG**

Postfach 13 57  
97803 Lohr, Germany  
Bgm.-Dr.-Nebel-Str. 2  
97816 Lohr, Germany  
Tel. +49 9352 18-0  
Fax +49 9352 18-8400  
[www.boschrexroth.com/electrics](http://www.boschrexroth.com/electrics)

**Local contact information can be found at:**

[www.boschrexroth.com/adressen](http://www.boschrexroth.com/adressen)

The data specified above only serve to describe the product. As our products are constantly being further developed, no statements concerning a certain condition or suitability for a certain application can be derived from our information. The information given does not release the user from the obligation of own judgment and verification.

It must be remembered that our products are subject to a natural process of wear and aging.